



DEPARTMENT OF TRADE AND COMMERCE
STANDARDS BRANCH

OTTAWA, November 25, 1963.

TYPE APPROVAL

PIONEER TYPES "IFB1A-5", "IFB1A-15", "IFB1B-5" and "IFB1B-15"

CURRENT TRANSFORMERS

The apparatus specified herein have been duly approved by the Standards Branch under the provisions of the Electricity Inspection Act, Chapter 94, R.S. 1952, and may be admitted to verification in Canada.


Apparatus Approved: Types "IFB1A-5", "IFB1A-15", "IFB1B-5" and "IFB1B-15"
Current Transformers manufactured by Pioneer Electric Limited, 101 Rockman Street, Winnipeg 19, Manitoba.

Rating of Apparatus:	
Primary Currents	10, 15, 20, 25, 30, 40, 50, 75, 100, 150, 200, 300, 400, 600, 800 amperes.
Secondary Current	5 amperes.
Voltage Rating	5 Kv and 15 Kv.
Accuracy Rating*	-5Kv.. 0.3B0.1, B0.2, B0.5, B0.9, B1.0, B(2 x 0.9); 0.6B2.0
	-15Kv. 0.3B0.1, B0.2, B0.5, B0.9, B1.0; 0.6B(2 x 0.9), B2.0
Wire	2
Frequency	60 cycles.

Accuracies apply up to 6.67 amperes of secondary current.

Description: These types are folded core current transformers encapsulated in epoxy. The windings consist of two primary coils connected in series, assembled over two corresponding secondary coils connected in parallel. The primary terminals are flat copper bars projecting from each end of the transformer and having one hole and one slot. The secondary terminals are brass inserts tapped 1/4-20 imbedded in the epoxy and into which are threaded 1/4-20 copper studs. The secondary terminals are located either on the top of the current transformer (Types IFB1A-) or in a shallow pocket in the base (Types IFB1B-). Polarity markings are raised white dots for primary and secondary. In addition, "X1" and "X2" are molded in relief adjacent to the secondary terminals.


R. W. MacLean,
Director,
Standards Branch.


E. F. Power,
Chief, Electricity & Gas Division,
Standards Branch

Ref: A-976B

