



DEPARTMENT OF TRADE AND COMMERCE
STANDARDS BRANCH



OTTAWA December 21, 1966.

NOTICE OF APPROVAL

FOR

CANADIAN WESTINGHOUSE TYPE "CSB-10" CURRENT TRANSFORMERS

Apparatus

Primary Currents	200, 400 and 600 amperes
Secondary Current	5 amperes
Accuracy Rating	
200 and 400 Amperes	0.3B0.1, 0.3B0.2*; 0.6B0.5*
600 Amperes	0.3B0.1, 0.3B0.2*; B0.5*; 0.6B0.9
Voltage Rating	600 volts
Rating Factor (R.F.)	
200 Amperes	2
400 and 600 Amperes	1.5
Phase	1
Wire	2
Frequency	60Hz
Style	Indoor/outdoor, moulded.

* Nameplate for all three ratios will be marked 0.3B0.2, 0.6B0.5.

Description

These ring type transformers are moulded in butyl rubber. Secondary lead connection is achieved by a compression type terminal block moulded into the top of the case. A removable spring clip inserted under the terminal screws serves as a shorting link. Reliable plastic caps may be supplied for weather proofing.

Polarity is indicated by depressed white filled letters H1 adjacent to the primary opening and X1 on the end of the terminal block. The metal nameplate also carries a polarity diagram.

This line of transformers manufactured in U.S.A. by Westinghouse Electric Corporation, consists of the following ratios: 200:5, 400:5 and 600:5 amperes.

In the original circular T-11 of April 29, 1966 the 200:5 and 400:5 amp ratios received approval with an accuracy rating of 0.3B0.1, B0.2 combined with a Rating Factor (R.F.) of 2. To permit the addition of 0.6B0.5 to the accuracy rating marked on the nameplate, the Rating Factor of the 400:5 ratio has been reduced from 2.0 to 1.5.

Some units may be encountered that have the nameplate marked 0.3B0.2 only, as illustrated.

Approval granted to: Canadian Westinghouse Company Limited,
London,
Ontario.

W. J. S. Fraser

W. J. S. Fraser,
Chief, Standards Laboratory,
Standards Branch.

K. Cryer

K. Cryer,
Chief, Electricity & Gas Division,
Standards Branch.

Ref: SL-100-57J

